

## MDT Switch Actuator compact 2/4/8/16-fold, MDRC

Version		
AKK-0216.03	Switch Actuator 2-fold	2SU MDRC, 230VAC, 16A
AKK-0416.03	Switch Actuator 4-fold	2SU MDRC, 230VAC, 16A
AKK-0816.03	Switch Actuator 8-fold	4SU MDRC, 230VAC, 16A
<b>AKK-1616.03</b>	<b>Switch Actuator 16-fold</b>	<b>8SU MDRC, 230VAC, 16A</b>

The MDT Switch Actuator AKK receives KNX/EIB telegrams and switches up to 16 independent electrical loads . Each output uses a bistable relay and can be operated manually via a push button. The outputs are parameterized individually via ETS. The device provides extensive functions like logical operation, status response, block functions, central function, delay functions and staircase lighting function. Additionally the device provides several time and scene control.

If the mains voltage fails, all outputs were switched off. After mains voltage recovery the relay position will be restored. After bus voltage failure or recovery the relay position is selected in dependence on the parameterization.


The MDT Switch Actuator AKK is a modular installation device for fixed installations in dry rooms. It fits on DIN 35mm rails in power distribution boards or closed compact boxes.

For project design and commissioning of the MDT Switch Actuator AKK it is recommended to use the ETS or later. Please download the application software at [www.mdt.de/downloads.html](http://www.mdt.de/downloads.html)

AKK-0216.03




AKK-0816.03



AKK-0416.03



**AKK-1616.03**



- Production in Germany, certified according to ISO 9001
- **Function extension:**
- Lockable manual operation and LED indicator for each channel
- NO and NC contact operation
- Status response after manually operation
- Time functions (switch-on/switch-off delay)
- Extensive staircase light and impulse function
- Status response (active/passive) for each channel
- Extended scene functions for each channel
- 8 scenes per channel
- Central switching functions and block functions
- Adjustable behavior in case of bus voltage failure or return
- Four contacts share one supply phase (AKK-02/0416.03)
- Each contact has an own supply phase (AKK-08/1616.03)
- Power supply via KNX bus
- Quick application download (long frame support for ETS5)
- Integrated bus coupling unit
- 3 years warranty

Technical Data	AKK-0216.03	AKK-0416.03	AKK-0816.03	AKK-1616.03
<b>Number of outputs</b>	2	4	8	16
<b>Output switching ratings*</b>				
Ohmic load	16A	16A	16A	16A
Capacitive load	70uF	70uF	70uF	70uF
Voltage	230VAC	230VAC	230VAC	230VAC
<b>Maximum inrush current</b>	300A/150µs 150A/600µs	300A/150µs 150A/600µs	300A/150µs 150A/600µs	300A/150µs 150A/600µs
<b>Maximum load</b>				
Incandescent lamps	2000W	2000W	2000W	2000W
Halogen lamps 230V	2000W	2000W	2000W	2000W
Halogen lamps, electronic transformer	1200W	1200W	1200W	1200W
Fluorescent lamps, not compensated	1800W	1800W	1800W	1800W
Fluorescent lamps, parallel comp.	800W	800W	800W	800W
Max. number of electronic transformers	10	10	10	10
<b>Output life expectancy (mechanical)</b>	1.000.000	1.000.000	1.000.000	1.000.000
<b>Max. total current of the actuator</b>	16A	16A	50A	100A
<b>Specification KNX interface</b>	TP-256 with long frame support for ETS5			
<b>Available application software</b>	ETS 4/5	ETS 4/5	ETS 4/5	ETS 4/5
<b>Permitted wire gauge</b>				
Screw terminal	0,5 - 2,5mm <sup>2</sup> solid core 0,5 - 2,5mm <sup>2</sup> finely stranded	0,5 - 4,0mm <sup>2</sup> solid core 0,5 - 2,5mm <sup>2</sup> finely stranded	1 x 0,5 - 4,0mm <sup>2</sup> solid core / finely stranded 2 x 0,5 - 2,5mm <sup>2</sup> solid core / finely stranded (no mix allowed)	
KNX busconnection terminal	0,8mm Ø, solid core	0,8mm Ø, solid core	0,8mm Ø, solid core	0,8mm Ø, solid core
<b>Torque screw terminal</b>	0,5Nm	0,5Nm	0,5Nm	0,5Nm
<b>Power supply</b>	KNX bus	KNX bus	KNX bus	KNX bus
<b>Power consumption KNX bus</b>	<0,3W	<0,3W	<0,3W	<0,3W
<b>Operation temperature range</b>	0 to +45°C	0 to +45°C	0 to +45°C	0 to +45°C
<b>Enclosure</b>	IP20	IP20	IP20	IP20
<b>Dimensions MDRC (Space Units)</b>	2SU	2SU	4SU	8SU

Exemplary circuit diagram AKK-0816.03

